

# Specifications Installation for the CM-9201-TM Calibration and Test unit for the CM-9201

## SPECIFICATIONS

<b>SIZE:</b>	2.25" x 2.25" x 1"
<b>WEIGHT:</b>	2.5 oz. (nominal)
<b>APPLIED IMPEDANCE:</b>	(Wrist Strap) Operator = 1.0 Meg (Impedance)
<b>ADJUSTMENTS:</b>	No user adjustments necessary
<b>CONTROLS:</b>	One Front Panel Push Button Switch

## TEST PROCEDURE:

1. Plug the test box ground side (Banana Male Plug) to common ground.
2. Plug the power supply as normal, to the CM-9201 power plug-in
3. Plug operator side of the test box into the CM-9201 monitor.
4. Press the operator test box push button switch operator led on the CM-9201D should change from a blinking red to green.
5. Release the operator test box push button and the operator led on the CM-9201D should change to a blinking red, with momentary beeps up to a maximum of 7 to 12 beeps.
6. If the monitor did not pass as per the test procedure. Call our Technical Support Hot Line at (877) 463-9376.

## CM-920TM INSTALLATION & TEST PROCEDURES

PRODUCT  
CM-920TM

ITEM NUMBER  
CM-920TM

DATA SHEET



**1-877-GND-ZERO** (463-9376)  
**FAX:** 941-751-7586  
4916 26<sup>TH</sup> Street West #100  
Bradenton, Florida 34207  
**EMAIL:** sales@gndzero.com  
[www.gndzero.com](http://www.gndzero.com)